

Single Phase Rectifier Bridge


PSB 71F

with fast Recovery Epitaxial Diode (FRED)

I_{dAV} = 68 A
 V_{RRM} = 400 - 600 V
 t_{rr} = 35 ns

Preliminary Data Sheet

V_{RSM}	V_{RRM}	Type
V_{DSM}	V_{DRM}	
(V)	(V)	
400	400	PSB 71F/04
600	600	PSB 71F/06



Symbol	Test Conditions	Maximum Ratings
I_{dAV}^*	$T_C = 85^\circ C$, (per module)	68 A
I_{dAVM}		90 A
I_{FSM}	$T_{VJ} = 45^\circ C$ t = 10 ms (50 Hz), sine	250 A
	$V_R = 0$ t = 8.3 ms (60 Hz), sine	275 A
	$T_{VJ} = T_{VJM}$ t = 10 ms (50 Hz), sine	215 A
	$V_R = 0$ t = 8.3 ms (60 Hz), sine	235 A
$\int i^2 dt$	$T_{VJ} = 45^\circ C$ t = 10 ms (50 Hz), sine	315 A ² s
	$V_R = 0$ t = 8.3 ms (60 Hz), sine	320 A ² s
	$T_{VJ} = T_{VJM}$ t = 10 ms (50 Hz), sine	230 A ² s
	$V_R = 0$ t = 8.3 ms (60 Hz), sine	230 A ² s
T_{VJ}		-40... + 150 °C
T_{VJM}		150 °C
T_{stg}		-40... + 125 °C
V_{ISOL}	50/60 Hz, RMS t = 1 min	3000 V~
	$I_{ISOL} \leq 1$ mA t = 1 s	3600 V~
M_d	Mounting torque (M4)	1.5 - 1.8 Nm
		14 - 16 lb.in.
Weight	typ.	16 g

Symbol	Test Conditions	Characteristic Value
I_R	$V_R = V_{RRM}, T_{VJ} = T_{VJM}$	≤ 1.0 mA
	$V_R = V_{RRM}, T_{VJ} = 25^\circ C$	≤ 0.25 mA
V_F	$I_F = 30$ A, $T_{VJ} = 25^\circ C$	≤ 1.57 V
V_{TO}	For power-loss calculations only	0.98 V
r_T		8 mΩ
R_{thJC}	per diode; DC	0.9 K/W
	per module	0.23 K/W
R_{thJK}	per diode; DC	1.2 K/W
	per module	0.3 K/W
I_{RM}	$I_F = 50$ A; $-di_F/dt = 100$ A/μs; $V_R = 100$ V L=0.05 mH; $T_{VJ} = 100^\circ C$	typ. 6 A
t_{rr}	$I_F = 1$ A; $-di_F/dt = 200$ A/μs; $V_R = 30$ V; $T_{VJ} = 25^\circ C$	typ. 35 ns
d_s	Creeping distance on surface	11.2 mm
d_A	Creeping distance in air	9.7 mm
a	Max. allowable acceleration	50 m/s ²

Data according to IEC 60747 refer to a single diode unless otherwise stated
 *- for resistive load at bridge output

Features

-
- Package with DCB ceramic base plate
- Isolation voltage 3000 V~
- Planar glass passivated chips
- Low forward voltage drop
- Leads suitable for PC board soldering
- UL registered, E 148688

Applications

- Supplies for DC power equipment
- Input and output rectifier for high frequency
- Battery DC power supplies
- Field supply for DC motors

Advantages

- Easy to mount with two screws
- Space and weight savings
- Improved temperature and power cycling capability
- High power density
- Small and light weight

Package style and outline

Dimensions in mm (1mm = 0.0394")

